

#### Quadplexer, dc bypass port 2, with 4.3-10 connectors

- New 4.3-10 connectors for improved PIM performance and size reduction
- Industry leading PIM performance
- Suitable for feeders cables reduction

OBSOLETE		
This product was discontinued on: December 30, 2024		
Replaced By:		
E14F15P13	Quadplexer 698-960/18/21/23-26, dc bypass on all ports, 4.3-10 connectors	


#### Product Classification

Product Type	Quadplexer	
General Specifications		
Product Family	CBC7182126	
Color	Gray	
Modularity	1-Single	
Mounting	Pole   Wall	
Mounting Pipe Hardware	Band clamps (2)	
RF Connector Interface	4.3-10 Female	
RF Connector Interface Body Style	Medium neck	
Dimensions		
Height	210 mm   8.268 in	
Width	250 mm   9.843 in	
Depth	68 mm   2.677 in	
Mounting Pipe Diameter Range	42.6-122 mm	



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 20, 2025

# Outline Drawing



# **Electrical Specifications**

#### Impedance

50 ohm

License Band, Band Pass

APT 700 | CEL 850 | CEL 900 | DCS 1800 | EDD 800 | IMT 2100 | IMT 2600 | LMR 800 | LMR 900

### Electrical Specifications, dc Power/Alarm

dc/AISG Pass-through, combiner	Branch 2
dc/AISG Pass-through, demultiplexer	Branch 2
Lightning Surge Current	5 kA
Lightning Surge Current Waveform	8/20 waveform

Page 2 of 4



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 20, 2025

### Electrical Specifications, AISG

AISG Carrier	2176 KHz ± 100 ppm
Insertion Loss, maximum	0.5 dB
Return Loss, minimum	10 dB

# **Electrical Specifications**

Sub-module	1	1	1	1
Branch	1	2	3	4
Port Designation	PORT 1 698-960	PORT 2 1710-1880	PORT 3 1920-2170	PORT 4 2300-2690
License Band	APT 700, Band Pass CEL 850, Band Pass CEL 900, Band Pass EDD 800, Band Pass LMR 800, Band Pass LMR 900, Band Pass	DCS 1800, Band Pass	IMT 2100, Band Pass	IMT 2600, Band Pass

# Electrical Specifications, Band Pass

Frequency Range, MHz	698-960	1710-1880	1920-2170	2300-2690
Insertion Loss, typical, dB	0.1	0.2	0.2	0.15
Return Loss, minimum, dB	18	18	18	18
Return Loss, typical, dB	20	20	20	20
Isolation, minimum, dB	50	50	50	50
Input Power, RMS, maximum, W	300	300	300	200
3rd Order PIM, typical, dBc	-160	-160	-160	-160
3rd Order PIM Test Method	Two +43 dBm carriers	Two +43 dBm carriers	Two +43 dBm carriers	Two +43 dBm carr


Two +43 dBm carriers Two +43 dBm carriers Two +43 dBm carriers Two +43 dBm carriers

## Block Diagram

Page 3 of 4



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 20, 2025



#### Mechanical Specifications

Wind Speed, maximum

216 km/h (134 mph)

### **Environmental Specifications**

Operating Temperature	-40 °C to +65 °C (-40 °F to +149 °F)	
Relative Humidity	15%-100%	
Corrosion Test Method	IEC 60068-2-11, 30 days	
Ingress Protection Test Method	IEC 60529:2001, IP67	
Vibration Test Method	IEC 60068-2-6	
Packaging and Weights		
Included	Mounting hardware	
Weight, net	5 kg   11.023 lb	



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 20, 2025

Page 4 of 4